

Public Address System & Speakers

LCS600 - PA/Air Horn/Aux Security Mic 100 Watt



LCS600

The LCS600 microphone control head features Public Address function, Air Horn, and either Radio Repeat function or 20 Amp Light Control relay. Also included are LED indicators for Power and Auxiliary function (Light Control or Radio Repeat function). On/Off/Volume is controlled with a rotary thumbwheel. The remote mount amplifier powers one 100 Watt speaker and includes the Light Control relay wiring and a remote Air Horn input with positive and negative switching options. The LCS600 features jumpers for option selections and is protected against speaker shorts with a self-resetting circuit and a high & low voltage shutdown feature. Ships complete with wire harness w/positive locking connector, mic clip, hardware, and instructions.

Specifications

Size: Handset: 3-3/4"H x 2-1/2"W x 1-1/2"D
 Amplifier Box: 1-3/4"H x 6"W x 5-3/4"D
Weight: 5 lbs.
Output: 100 Watts
Voltage: 10V - 16V DC (24V available)
Frequency: 675-1633Hz
Amp Draw: 8 Amps

All Speakers have an Output of 100 Watts and an Impedance of 11 Ohms



D-10

Designed for exterior mounting. Grey fiberglass bell housing gives wide angle sound dispersion while providing high weather resistance.

Size: 12" L / 14" W / 6" H



D-40

Ultra thin, fits in tight places. Solid cast aluminum, works with a wide variety of sirens. Class A, Article 8 Title 13 compatible.

Size: 6.5" Dia. / 2.25" Depth



D-60

Bell housing made of high-impact ABS plastic. Speaker can be mounted almost anywhere.

Size: 7.25" L / 8" W / 5.25" H

